



Belastung und Ohmwerte

Nr.	Amp.	Typ 50 Ω	Typ 80 Ω	Typ 120 Ω	Nr.	Amp.	Typ 50 Ω	Typ 80 Ω	Typ 120 Ω
0	0.05	7500			11	1	70	170	300
0	0.1	3500	10000	18000	12	1.2	48	120	200
1	0.175	1900	4800	8600	13	1.4	35	80	150
2	0.2	1400	3600	6500	14	1.7	25	60	100
3	0.3	1000	2500	4500	15	2	17	40	70
4	0.35	700	1800	3200	16	2.5		30	54
5	0.4	500	1300	2300	17	2.8		20	36
6	0.5	360	900	1600	18	3.4		15	27
7	0.6	250	650	1200	19	4		12	18
8	0.7	200	480	860	20	4.8		10	14
9	0.8	135	330	600	21	5.5		7.5	10
10	0.9	100	230	400	22	6.5		5	8